

PA AMP120XL



Technical Specifications

Output power RMS / MAX: 60/90W

Inputs: 4x MIC/LINE balanced - 1x AUX (CD/TAPE/TUNER selectable)

Input Sensitivity: MIC: 2mV / 600 ohm (with 24V phantom)
-LINE: 100mV / 100 Kohm -AUX: 150mV / 10 Kohm

Signal Output: TAPE OUT

Output Levels: TAPE OUT: 300mV / 4.7 Kohm

Controls: 1 MASTER VOLUME CONTROL - 4 MIC/LINE VOLUME CONTROLS
1 BASS TONES CONTROL

Loudspeakers outputs: 100/70/50V - 4 ohm

Frequency response: 50Hz - 18KHz (-3dB)

Distortion (THD): < 1% (@ Phom 1KHz)

S/N Ratio: > 80dB

Power Supply: 230/117Vac 50/60Hz - 24Vdc for Emergency

Operating temperature: 0 - 40°C

Input/Output Connectors: MIC/LINE: 4x XLR -AUX: 1x RCA L/R
-TAPE OUT: 1x RCA L/R -OTHERS IN/OUT: screw terminals

Dimensions (W x H x D): 420 x 88 x 280mm - 2 rack unities 19"

Weight: 7.8Kg (17.199 lb)

120W MIXER AMPLIFIER.

Amplifier with tone controls

Category: Public Address » Amplifiers

Brand: PROEL

Product Code: PA AMP120XL

Overview

AMP Proel amplifiers series have been designed for mixing and microphone announcement diffusion in PA applications. Main features:

- Protection circuit for the speakers against overload and short circuit
- Led Power indicator
- Led level indicator
- Main volume control
- Separate volume control for inputs from 1 to 5
- Low and high tone control
- Ground connection screw
- Four mic/line microphone with XLR (Phantom24V)
- Three AUX inputs rear switchable
- Main in/out function
- Four outputs amongst which one at 4 ohm constant impedance and the other three at constant voltage (25/50/100V)
- TAPE OUT output on RCA
- Power switch selector 230V/117Vca
- 24Vdc emergency power supply
- Supplied by Proel with brackets for rack mounting purposes
- Rack mount brackets included
- Microphone input with priority function and apt to receive microphone stand BM100 and BMGONG chime

Related Products



PA AMP240V4

PA AMP30XL

PA AMP60XL

Prodotti Complementari



PA BM100